

# PowerWalker VFI 1500RT LCD

Online UPS

1500VA Online UPS with 0.9 Output Power Factor

2-in-1 Rack/Tower Design with LCD display

8 IEC Outlets, Dry contacts (in/out), EPO function

USB & RS-232 Connection for monitoring

Optional: SNMP module, AS/400 card, Modbus Card, MBS, ATS, Rack installation kit, Battery Pack



Item-No. 10120121





## Product Features

With true double-conversion online UPS design, PowerWalker VFI 1500RT provides powerful and overall protection to your sensitive devices. It can accept wide input voltage for harsh environment. It offers full protection for critical devices such as sensitive servers, network/telephone communication systems as well as for industrial applications.

With its slim design it only requires 2U valuable space of your rack system. The UPS can be installed in 19" rack systems or used as tower.

- True double-conversion with pure sine wave output
- Output power factor 0.9
- Monitoring software included
- Wide input voltage range (120-276 VAC)
- Input power factor correction
- Input THDi <5%, Output THDv <2%
- 50/60 Hz frequency converter mode
- ECO mode operation for energy saving
- Programmable power management outlet
- Emergency power off (EPO) function
- Intelligent fan control for reduced noise level
- Smart battery charger to extend battery life
- Optional: Rack installation kit, SNMP module, dry contact AS/400 card, Modbus card, Battery Pack, MBS, ATS



## Technical Details

### Product Features

Capacity	1500VA/1350W
----------	--------------

### Input

Voltage Range (based on voltage range)	120-276VAC Depends on Load Level
Frequency Range	45-55Hz/54-66Hz
Power Factor	≥ 0.99 at Full Load

### Output

Voltage	208/220/230/240 ± 1%
Frequency (Synchronized Range)	45-55Hz/54-66Hz
Frequency (Battery Mode)	50/60Hz ± 0.2%
Current Crest Ratio	3:1
Harmonic Distortion	≤ 2% (Full Linear Load)
Waveform	Pure Sine Wave

### Transfer Time

AC to DC	Zero
Inverter to Bypass	Zero
Inverter to ECO	1ms
ECO to Inverter	<10ms

### Battery

Type	12V / 7.2Ah
Quantity	4x
Backup Time (full load)	>4 Minutes
Recharge Time	3h to 90%

### Overload capability

Line Mode or Battery Mode	12s @102%-130%
	1.5s @130%-150%
	100ms @ >150%

### Bypass

Before UPS	Default "No"
Power-on	Change to "Yes" via display panel
Overload und UPS Failure	Automatically transfer to bypass
By Setting	Voltage Rang: 120-276V ± 3%

### LCD Display (direction swappable)

LCD Indicators	UPS status, Load level, Battery level, Input/Output voltage, AC mode, battery mode, Bypass mode, fault conditions
Display colour	Blue, red, red flashing (depends on UPS status)

### Audio Indicators

4 Modes	See manual for details
---------	------------------------

### Connections

Communication	USB & RS-232 port
Outlets	8x IEC (programmable)
Intelligent Slot	Yes
Dry contact	Yes (in/out)
EPO	Yes

### Software & System Requirements

Software	Winpower
Operating System	For details visit: <a href="http://www.powerwalker.com/winpower.html">http://www.powerwalker.com/winpower.html</a>

### Product Details

Dimensions	438 x 436 x 86.5 mm
Colour	Black
Weight	19.7 kg
Fan Control	Always on, automatic speed control
Noise Level	< 45dB at 1 Meter
Model Code	VFI 1500RT LCD

### Environment

Temperature	0°C – 40°C
Humidity	0 - 95% (non-condensing)

### Package Content

Package Content	PowerWalker VFI 1500RT LCD, Input Power Cord, 2x IEC cable, USB and RS-232 cable, Software CD, Tower holder, Rack ears, EPO plug, Dry contacts plug, manual
-----------------	---

### Logistic Data

Giftbox Language	EN
Manual Language	EN
Dimension/Giftbox	535 x 535 x 215 mm
Weight/Giftbox	22.7 kg
Pieces/Carton	1
Pieces/Palette	16
Item Number	10120121
EAN-Code	4260074974409
Warranty	24 Month (except battery)

Use UPS configurator on [www.powerwalker.com](http://www.powerwalker.com) for detailed backup time information.

Version: EN 26/08/2014  
We reserve the right for technical changes and mistakes

## Optional Accessories



NMC Card (SNMP module)  
Datasheet: [Link](#)  
Item No.: 10120517



EMD for NMC Card  
Environmental Monitoring Device  
Monitor Temperature & Humidity  
Datasheet: [Link](#)  
Item No.: 10120545



CMC Card (Modbus Card)  
Datasheet: [Link](#)  
Item No.: 10120564



AS/400 Card  
Datasheet: [Link](#)  
Item No.: 10120528



19" Rack-Mount-Kit  
Datasheet: [Link](#)  
Item No.: 10120529



3x Yuasa 12V/9Ah battery  
Datasheet: [Link](#)  
CSB or Panasonic brand can also be used




3x Yuasa 12V/7Ah battery  
Datasheet: [Link](#)  
CSB or Panasonic brand can also be used

RS-232 cable  
Item Nr.: 91010012



Battery Pack with inside 2x Battery Sets  
(Each battery set contain 4x 12V/7.2Ah batteries)  
Datasheet: [Link](#)  
Item No.: 10120536  
Possible to connect up to 9 Battery Packs



Battery Set with 4x 12V/7Ah batteries  
(Plug-and-Play solution incl. case and cabling to change internal bat. Set of VFI 1500RT LCD)  
Datasheet: [Link](#)  
Item No.: to be checked



USB cable  
Item Nr.: 91010011



ATS (Automatic Transfer Switch)  
Datasheet: [Link](#)  
Item No.: 10120543



19" MBS  
Maintenance Bypass Switch  
Datasheet: [Link](#)  
Item No.: 10120501



MBS (Maintenance Bypass Switch)  
Datasheet: [Link](#)  
Item No.: 10120500



Schuko Input -> IEC C13  
Item Nr.: 91010017



UK Input -> IEC C13  
Item Nr.: 91010029

Swiss Input -> IEC C13



IEC C13 -> IEC C14  
Item Nr.: 91010013



Schuko Input -> IEC C19  
Item Nr.: 91010018

UK Input -> IEC C19  
Item Nr.: 91010030

Swiss Input -> IEC C19



IEC C19 -> IEC C20  
Item Nr.: 91010028



IEC C13 -> IEC C20  
Item Nr.: 91010041



IEC C14 -> IEC C19  
Item Nr.: 91010040



IEC C14 -> Schuko  
Converter  
Item Nr.: 91015003



Schuko -> UK adaptor  
Item Nr.: 91010031